

BWR-71 USB Bluetooth Wireless Receiver

Product Code BWR-71

Our new BWR-71 USB Bluetooth 5.0 (LE) wireless receiver is designed specifically to provide long range reliable control of a Windows based PC.

Circumventing Windows' native management of Bluetooth devices and associated drivers, the BWR-71 presents itself as a Human Interface Device (HID), the same as wireless mice and keyboards. This type of interface provides consistent, reliable operation even when frequent Windows updates are applied via the internet.

Compatible with both Windows 10 and 11 operating systems, the BWR-71, in conjunction with our new RFC-96 Bluetooth 5.0 remote control, can be used with either our dedicated Boston control software or as a simple plug-and-play PC remote control for all other Windows applications.

Furthermore, the BWR-71 is also available in several other configurations providing analogue, digital and Modbus outputs for connection to other types of equipment.

BWR-71 also works in conjunction with our new wireless Play Detector torch control BTC10W, and is reverse compatible with legacy products to enable ongoing operation of old equipment.



Product Features

- ✓ Latest Bluetooth 5.0 (LE) technology
- ✓ Long range operation of 50m+
- ✓ USB powered from a PC
- ✓ Small compact design
- ✓ Internal ND magnet for convenient placement
- ✓ Easy-clean membrane keypad
- ✓ Quick plug & play installation
- ✓ Simple two button pairing procedure
- ✓ Compatible with multiple Boston products
- ✓ Can be used as a wireless receiver for other hardware applications
- ✓ Designed and manufactured in the UK
- ✓ 2 year warranty
- ✓ OEM enquiries welcome

BWR-71 USB Bluetooth Wireless Receiver

Technical Specifications

	BWR-71
Power	5V DC - USB Supply
Electronics	Microprocessor Controlled
Communication	Bluetooth 5.0 (LE)
Range	50m +
Mounting Mechanism	Neodymium Magnet
Installation	Plug & Play (no drivers required)
Operation	Membrane Keypad
Compatibility (RFC-96 required)	Windows 10 / 11 (all applications)
Manufactured	UK
Warranty	2 Years

Measurements (millimetres)

	BWR-71
Dimensions (L x W x H)	110 x 74 x 25 mm